

ESI OPTIONAL FEATURE CODES:

THE FOLLOWING OPTIONAL FEATURES MAY BE ACCESSIBLE FROM YOUR STATION. IN EACH CASE, YOU MUST USE A PROGRAMMABLE FEATURE KEY.

1. Note: In the codes below, **XXX** = represents the extension number to forward to.

CODE	FEATURE KEY
560	Manual Day/Night Mode
561	Service Observing
564	Headset Key
565	Call Forward Key
565 XXX	Forward to a Destination
566	Redial
567	Call Forward/No-Answer Key
568	Message Monitor Key
569	Background Announce Key
570	Conference
571	Personal Greeting 1
572	Personal Greeting 2
573	Personal Greeting 3
574	Caller ID Key
575 & 576	Virtual Answer Keys
577	Quick Page
578	Mute/DND
579	Voice Mail
580	Override Ring Key
582	Record
583	Quick Switch
584	Account Codes
587	Loop Key
599	Overhead Page

Manual Day/Night Mode (Code 560)

You can use a programmable feature key to manually change the system's main auto attendant greeting, incoming call destinations and CO line group access. Each time the key is pressed, the display switches among: DAY, NGT, DAY2, NGT2, HDY (Holiday) OR AUTO.

Tip: To keep the system from being taken out of this mode, place it in auto and then delete the programmable feature key's programming.

Note: The system administrator can also change the mode and/or re-record the holiday greeting remotely to handle unexpected closings, such as for inclement weather.